

# **Open Source LoRaWAN Gateway**





# **OVERVIEW:**

The LG308N is an open source LoRaWAN Pico Gateway. It lets you bridge LoRa wireless network to an IP network via WiFi, Ethernet, 3G or 4G cellular network. The LoRa wireless allows users to send data and reach extremely long ranges at low data-rates.

The LG308N uses Semtech packet forwarder and fully compatible with LoRaWAN protocol. It includes a SX1302 LoRa concentrator, which provides 10 programmable parallel demodulation paths.

LG308N has pre-configured standard LoRaWAN frequency bands to use for different countries. User can also customized the frequency bands to use in their own LoRa network.

LG308N can communicate with ABP LoRaWAN end node without LoRaWAN server. System integrator can use it to integrate with their existing IoT Service without set up own LoRaWAN server or use 3rd party LoRaWAN service.

#### Features:

- LoRaWAN Gateway
- Open Source Linux system
- Emulates 49x LoRa demodulators
- Managed by Web GUI, SSH via LAN or WiFi
- 10 programmable parallel demodulation paths

### **Applications:**

- Smart Metering
- Smart Agriculture
- Smart Cities
- Smart Factory
- Smart Buildings & Home Automation
- Logistics and Supply Chain Management

## Specifications:

LoRa Interfaces:

- 1 x SX1302 + 2 x 1250 LoRa Transceiver
- Max Output Power: 27dBm
- Sensitivity: -142.5dBm

#### General Interfaces:

- 10M/100M RJ45 PoE Port x 2
- WiFi: 802.11 b/g/n
- 1 x USB host port
- 1 x Mini-PCle Interface
- Power Input: 12v DC, 2A
- LoRaWAN Wireless

### Order Info: LG308N-XXX-YYY

XXX: Frequency Band

- 868: For EU868, IN865
- 915: For US915, AU915, AS923 ,KR920

#### YYY: 4G Cellular Option

- EC25-E: EMEA, Korea, Thailand, India
- EC25-AFX: America:Verizon, AT&T(FirstNet), U.S.Cellular; Canada:Telus
- EC25-AUX: Latin America, New Zeland, Taiwan
- EC25-J: Japan, DOCOMO, SoftBank, KDDI

# Dragino Technology Co., Limited

Room 202, Block B, BCT Incubation Bases (BaoChengTai), No.8 CaiYunRoad LongCheng Street, LongGang District ; Shenzhen 518116,China Direct: +86 755 86610829 |Fax: +86 755 86647123

### WWW.DRAGINO.COM sales@dragino.com